



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: +(773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: PV2000FC

### PowerVerter® Plus 2000W Industrial-Strength Inverter with 2 Outlets



#### Highlights

- Designed for heavy duty and motor loads
- 12V DC input; 120V AC output; 2 outlets
- 2000W continuous output
- Peak surge output: OverPower (up to 1 hour)—3000W, Double-Boost (up to 10 seconds)—4000W
- High-efficiency power conversion
- Automatic overload protection

#### Description

Utilize your vehicle's battery to efficiently power office equipment on the road or power tools at a work site. Continuously supplies up to 2000W of 120V AC power to 2 AC outlets from any 12V battery or automotive DC source. Frequency control locks AC output at 60Hz for operating stability of motor loads. Includes a set of high-current DC input terminals for simple, permanent installation. Highly reliable large transformer design specializes in powering motors and other inductive loads with high-current startup needs. Built-in RJ45 port allows connection of APS/PowerVerter Remote Switch (Tripp Lite # [APSRM4](#))

OPTIONAL FEATURES: Optional load sense function enables automatic inverter shutoff and startup as connected equipment is powered off and on. Front panel load sense potentiometer can be set to shut off or turn on inverter power in response to loads of any level. Ignition Switch Control Jack connects inverter to vehicle ignition system to automatically control inverter. Inverter ON/OFF Relay Jack connects to a user-supplied on/off indicator for remote visual status of the operation of the inverter.

#### Applications

- Ideal for industrial power tools, window air conditioners, electric motors, pumps, desktop computers, laptops, portable electronics, battery chargers for cell phones and games, large-screen TV/DVD/stereo systems, camcorders, lighting and other AC applications under 2000W continuous/ 4000W peak.

#### Package Includes

- PV2000FC Inverter
- Instruction manual

#### Features

- Allows users to run large, motorized AC appliances from any 12V battery or automotive DC system
- Converts 12V DC battery power to 120V AC power
- 2000W continuous output power
- Peak surge output: OverPower (up to 1 hour) 3000W, Double-Boost (up to 10 seconds) 4000W
- 2 x NEMA 5-15/20R outlets; DC input terminals for 12V battery connection
- Frequency control for operating stability
- High-efficiency operation conserves batteries to prolong runtime

- Diagnostic LEDs indicate load level (high, medium, and low) and battery charge (high, medium, and low)
- DC fusing protects inverter against overload
- High-impact polycarbonate housing
- RJ45 port allows connection of APS/PowerVerter Remote Switch (Tripp Lite # [APSRM4](#))
- Grounding lug properly connects the inverter system to earth ground or vehicle grounding system
- Load sense function enables automatic inverter shutoff and startup as connected equipment is powered off and on.

## Specifications

OVERVIEW	
Intended Application	Utility/Long-Haul Truck; RV/Marine
OUTPUT	
Frequency compatibility	60 Hz
Output watts	2000
Continuous output capacity (watts)	2000
Peak output capacity (watts)	4000
Output nominal voltage	120V
Output voltage regulation	Maintains PWM sine wave output voltage of 120 V AC (+/-5%)
Output frequency regulation	60 Hz (+/- 0.3 Hz)
Overload protection	Circuit breaker
Outlet quantity / type	2 NEMA 5-15R
INPUT	
Recommended Electrical Service	Requires 12V DC input source capable of delivering 200A for the required duration (when used at full capacity). For automotive applications, professional hardwire installation with 400A battery system fusing is recommended
Maximum input amps / watts	Full continuous load - 200A at 12V DC, No load - 2.2A at 12V DC
Input connection type	Set of 2 DC bolt-down wiring terminals
Input cord length details	User supplies cabling; 2/0 gauge or larger recommended
Voltage compatibility (VDC)	12
BATTERY	
DC system voltage (VDC)	12
LEDS ALARMS & SWITCHES	
Switches	3-position on/off/remote switch enables simple on/off power control plus "remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional <a href="#">APSRM4</a> accessory
Front panel LEDs	Set of 6 LEDs offers continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences
PHYSICAL	

Shipping Dimensions (HWD/in)	13.5 x 15 x 21.5
Shipping Dimensions (HWD/cm)	34.29 x 38.1 x 54.61
Shipping weight (lbs)	43
Shipping weight (kg)	19.5
Unit Dimensions (HWD/in)	7.25 x 8.5 x 16.25
Unit Dimensions (HWD/cm)	18.42 x 21.59 x 41.28
Unit weight (lbs)	39.0
Unit weight (kg)	17.7
Cooling method	Fan
Material of construction	Polycarbonate
Style	Heavy-duty
Form factors supported	Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional mounting information)
<b>ENVIRONMENTAL</b>	
Relative Humidity	0-95% non-condensing
<b>SPECIAL FEATURES</b>	
Appearance	Attractive all-black color scheme
Load Sensing	Optional load sense function enables automatic inverter shutoff and startup as connected equipment is powered off and on. Front panel load sense potentiometer can be set to shutoff or turn on inverter power in response to loads of any level
Remote control capability	Yes
<b>CERTIFICATIONS</b>	
Certifications	Meets UL458 (USA, Canada), RoHS Compliant
<b>WARRANTY</b>	
Product Warranty Period (Worldwide)	1-year limited warranty

## Related Items

### Optional Products

Related Model	Description	Qty.
<a href="#">APSRM4</a>	Remote Control Module - for Tripp Lite Inverters and Inverter/Chargers	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/en/products/model.cfm?txtModelID=181](http://www.tripplite.com/en/products/model.cfm?txtModelID=181).