



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: +(773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: UT750UL

### PowerVerter® 750W Utility/Work Truck Inverter with 2 Outlets

#### Highlights



- 12V DC or 120VAC input; 120VAC output; 2 **GFCI** protected outlets
- 750 watts continuous, 1125 watts OverPower and 1500 watts
- DoubleBoost inverter output
- 3 stage, 45A / 11A selectable wet / gel / AGM cell battery charger
- Built-in Isobar® premium AC surge protection and Auto Transfer
- Switching option for battery backup / UPS operation
- Meets OSHA requirements

#### Description

Tripp Lite UT750UL Utility Work Truck Inverter / Charger are the quiet alternative to gas generators with no fumes, fuel or noise. It provides equipment with utility or generator supplied AC electricity filtered through premium ISOBAR surge protection. This DC-to-AC inverter with automatic line to battery transfer and integrated charging system serves as an extended run UPS, a standalone power source or an automotive inverter suitable for rugged work site applications. Supplies up to 750 watts of continuous 120V AC power from any 12V DC battery or automotive DC source. OverPower inverter output feature temporarily provides up to 150% of the continuous output for 1-60 minutes, and DoubleBoost inverter output feature delivers up to 200% of continuous output for up to 10 seconds, providing the extra power needed to start heavy-duty tools and motorized equipment. When AC cable is connected to a live wall socket, commercial power passes through to connected equipment and the battery set is recharged via 3 stage selectable 11/45Amp charging system. In UPS mode, the APS system responds to blackouts and voltage fluctuations with a near instantaneous automatic transfer to battery derived AC output. A set of high current DC input terminals is included for simple installation (user supplies batteries and cabling – see owners manual for recommendations). Passes sine wave utility or generator power during battery charging and UPS line power operation, plus efficient PWM sine wave AC output in inverter and UPS backup modes. Reliable large transformer design, with frequency control, powers resistive electronic loads or large inductive motors, compressors and other devices with high current needs on startup. Included is the APSRM4 wired remote power switch with full status LED's, which provides remote power inverter on/off switching and continuous status information. The UT750UL supports an unlimited amount of runtime with user-supplied batteries.

#### Applications

Versatile inverter / charger system with auto-transfer switching serves as an automotive inverter for utility work trucks, conversion vans and fleet service vehicles; a standalone power source for off grid, alternative energy or export applications, emergency home power applications such as sump pumps, and as an uninterruptible power supply (UPS) for items compatible with a 16.6 millisecond transfer time.

#### Package Includes

- UT750UL Inverter/Charger
- APSRM4 Remote
- Instruction manual with warranty information

#### Features

- 16.6 millisecond automatic transfer between line and battery power supports UPS protection for equipment compatible with a one cycle transfer time
- 750W continuous AC output in inverter mode, 1500W continuous AC output in AC mode
- DoubleBoost output supports momentary startup loads of up to 200% of the continuous rating for up to 10 seconds - OverPower output supports duration overloads to 150% for 1-60 minutes under ideal battery and temperature conditions
- 3-stage selectable 11/45 Amp battery charger with adjustable settings for wet/gel/AGM battery types
- 2 NEMA 5-15R GFCI protected outlets pass 120V line power or inverter output through to connected equipment
- 3 position operating mode switch supports "AUTO" mode to enable automatic transfer between DC and AC modes, CHARGE ONLY to

maintain a full battery charge when AC is present without auto transfer and SYSTEM OFF settings

- Set of 6 front panel LED's display continuous status
- Set of 4 dip switches support wet/gel/AGM battery charging profiles, adjustable 135/145V high voltages and selectable 75/85/95/105V AC low voltage auto transfer during brownouts
- Set of 4 additional dip switches support 4 levels of charger limiting relative to output load size, a battery equalization program and battery charger low/high settings
- Resettable 10A charger AC input breaker and settable 12A AC output breaker and automatic 2-speed cooling fan
- Automatic overload and thermal (overheating) shutoff
- Front panel remote control connector enables remote off/on switching with included APSRM4 remote
- Load sensing control dial enables adjustable load threshold required to automatically turn the inverter on and off in DC mode as load conditions change

## Specifications

OVERVIEW	
<b>Intended Application</b>	Utility/Long Haul Truck, Emergency Home Power
OUTPUT	
<b>Frequency compatibility</b>	60 Hz
<b>Output watts</b>	750
<b>Continuous output capacity (watts)</b>	750
<b>Peak output capacity (watts)</b>	1500
<b>Output nominal voltage</b>	120V
<b>Output voltage regulation</b>	LINE POWER (AC): Maintains 120V nominal sine wave output from line Source. Inverter Power (AC) Maintains PWM sine wave output voltage of 120 VAC (+/- 5%)
<b>Output frequency regulation</b>	60 Hz (+/- 0.3Hz)
<b>Overload protection</b>	Includes 10A input breaker dedicated to the charging system and 12A output breaker for AC output loads.
<b>Outlet quantity / type</b>	2 NEMA 5-15R outlets
<b>Outlet details</b>	2 NEMA 5-15R GFCI protected outlets
INPUT	
<b>Nominal Input Voltage(s) Supported</b>	120V AC
<b>Recommended Electrical Service</b>	DC INPUT: Requires 12VDC input source capable of delivering 73A for the required Duration (when used at full continuous capacity- DC requirements increase during Over-Power and Double-Boost operation). AC INPUT: 15A 120VAC recommended.
<b>Maximum input amps / watts</b>	DC INPUT: Full continuous load of 73A at 12 VDC. AC INPUT 29 amps at 120 VAC with full inverter and charger load (9.3A max charger only / combined input load to support charger and AC output is automatically controllable to 66% - 33% - 0% based on AC)
<b>Input connection type</b>	DC INPUT: set of two (2) DC bolt-down terminals. AC INPUT: NEMA 5-15R GFCI input plug
<b>Input cord length details</b>	DC INPUT: User supplies cabling. 6 gauge or larger (see manual) AC INPUT: attached 6ft. AC line cord with plug.
<b>Voltage compatibility (VAC)</b>	120

Voltage compatibility (VDC)	12
<b>BATTERY</b>	
Expandable battery runtime	Runtime is expandable with any number of user supplied wet or gel or AGM type Batteries.
DC system voltage (VDC)	12
Battery Pack Accessory (optional)	<a href="#">98-121</a> sealed lead acid battery (optional)
Battery charge	11A / 45A (selectable)
<b>LEDS ALARMS &amp; SWITCHES</b>	
Switches	3 position on / off remote switch enables simple on / off power control plus "auto/ remote" Setting that enables distant on / ff control of the inverter system when used in conjunction with <a href="#">APSRM</a> remote (included) when used in inverter mode AC uninterrupt
Front panel LEDs	Set of (6) LEDs offer continuous status information on load percentage ( 6 levels reported) and battery charge level (7 levels reported) See manual for sequences
<b>SURGE / NOISE SUPPRESSION</b>	
AC suppression joule rating	450
<b>PHYSICAL</b>	
Shipping Dimensions (HWD/in)	12.5 x 11 x 10.75
Shipping Dimensions (HWD/cm)	31.75 x 27.94 x 27.31
Shipping weight (lbs)	20.6
Shipping weight (kg)	8.2
Unit Dimensions (HWD/in)	7 x 8.75 x 9
Unit Dimensions (HWD/cm)	17.78 x 22.23 x 22.86
Unit weight (lbs)	17.4
Unit weight (kg)	7.9
Cooling method	Multi-speed fan
Material of construction	Polycarbonate
Receptacle Color	White
Style	Heavy-duty with built-in battery charger
Form factors supported	Mounting slots enable permanent placement of inverter on any horizontal surface. (see manual for additional mounting information)
<b>ENVIRONMENTAL</b>	
Relative Humidity	0-95% non-condensing
<b>LINE / BATTERY TRANSFER</b>	

<b>Transfer time from line power to battery mode</b>	16.6 milliseconds (typical -compatible with many computers, servers and networking equipment-verify transfer time compatibility loads for UPS applications)
<b>Low voltage transfer to battery power</b>	In AC "auto" mode, inverter / charger switches to battery mode as line voltage drops to 75V (user adjustable to 85,95,105 - see manual)
<b>High voltage transfer to battery power</b>	In AC "auto" mode, inverter / charger switches to battery mode as line voltages increases to 145V (user adjustable to 145 - see manual)
<b>SPECIAL FEATURES</b>	
<b>Load Sensing</b>	Load sense function enables automatic inverter shutoff and startup as connected equipment is powered off and on. Front panel load sense potentiometer can be set to shutoff or turn on inverter power in response to loads of any level.
<b>Remote control capability</b>	Yes
<b>CERTIFICATIONS</b>	
<b>Certifications</b>	Tested to UL 458 (USA) and CSA (Canada)
<b>WARRANTY</b>	
<b>Product Warranty Period (U.S. &amp; Canada)</b>	30-month limited warranty
<b>Product Warranty Period (International)</b>	1-year limited warranty
<b>Product Warranty Period (Mexico)</b>	30-month limited warranty
<b>Product Warranty Period (Puerto Rico)</b>	30-month limited warranty

## Related Items

### Optional Products

Related Model	Description	Qty.
<a href="#">APSRM4</a>	Remote Control Module - for Tripp Lite Inverters and Inverter/Chargers	1
<a href="#">BP-260</a>	Ideal battery housing for use with Tripp Lite PowerVerter APS inverter/charger systems with a 12 or 24V DC system voltage.	1
<a href="#">98-121</a>	12V DC Sealed, Maintenance-Free Battery	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/en/products/model.cfm?txtModelID=3604](http://www.tripplite.com/en/products/model.cfm?txtModelID=3604).

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.