	UB25	0-F77-	-E0-V31
--	-------------	--------	---------

	Technical data	
	General specifications	
S. Wa	Sensing range	20 250 mm
Barry En	Adjustment range Unusable area	45 250 mm 0 20 mm
A REAL PROPERTY AND	Standard target plate	20 mm x 20 mm
AN STR.	Transducer frequency	approx. 400 kHz
241 Mar C .	Nominal ratings	< 150 mm
Contraction of the second	Time delay before availability t _v	≤ 150 ms
	Permissible cable length	max. 300 m
	Indicators/operating means	
	LED yellow	switching state and flashing: Teach-In
	Electrical specifications Rated operating voltage U _e	24 V DC
	Operating voltage U _B	20 30 V DC , ripple 10 % _{SS} ; 12 20 V DC sensitivity
		reduced to 90 %
	No-load supply current I0	≤ 20 mA
	Input	
	Input type Level	1 program input low level : 0 0.7 V (Teach-In active)
		high level : U _B or open input (Teach-In inactive)
lodel Number	Input impedance	16 kΩ
B250-F77-E0-V31	Pulse length	≥3 s
	Output Output type	1 switch output E0, NPN, NO
Itrasonic direct detection sensor	Rated operating current I _e	200 mA , short-circuit/overload protected
	Voltage drop U _d	≤2 V
eatures	Switch-on delay t _{on}	\leq 50 ms
Miniature design	Repeat accuracy	± 1 mm
Program input	Switching frequency f Range hysteresis H	10 Hz typ. 2.5 mm
	Off-state current I _r	≤ 0.01 mA
Degree of protection IP67	Temperature influence	+ 0.17 %/K
Switching status indicator, yellow	Ambient conditions	
LED	Ambient temperature Storage temperature	-25 70 °C (-13 158 °F) -40 85 °C (-40 185 °F)
	Shock resistance	30 g , 11 ms period
liagrams	Vibration resistance	10 55 Hz , Amplitude ± 1 mm
	Mechanical specifications	
haracteristic response curve	Connection type Degree of protection	M8 x 1 connector , 4-pin IP67
stance Y [mm]	Material	11 07
	Housing	Polycarbonate
	Transducer	epoxy resin/hollow glass sphere mixture; polyurethane foar
	Installation position Mass	any position 10 g
	Tightening torque, fastening screws	max. 0.2 Nm
	Compliance with standards and	
	directives	
	Standard conformity	
	Standards	EN 60947-5-2:2007 IEC 60947-5-2:2007
	Approvals and certificates	
0 50 100 150 200 250 300 Distance X [mm]	UL approval	cULus Listed, General Purpose
Distance X [mm]	CSA approval	cCSAus Listed, General Purpose
ťŸ	CCC approval	CCC approval / marking not required for products rated
		≤36 V
	1	

Release date: 2013-02-28 14:23 Date of issue: 2014-05-15 252742_eng.xml

 Refer to "General Notes Relating to Pepperl+Fuchs Product Information".

 Pepperl+Fuchs Group
 USA: +1 330 486 0001
 G

 www.pepperl-fuchs.com
 fa-info@us.pepperl-fuchs.com
 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411 fa-info@de.pepperl-fuchs.com


Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com




1

UB250-F77-E0-V31

Dimensions



Electrical Connection



Pinout



Wire colors in accordance with EN 60947-5-2

1	BN	(brown)
2	WH	(white)
3	BU	(blue)
4	BK	(black)



2

Accessories

UB-PROG4-V31

Programming unit for ultrasonic sensors with Teach-in input at pin 2

OMH-ML7-01 Mounting bracket

V31-GM-2M-PVC Female cordset, M8, 4-pin, PVC cable

V31-WM-2M-PVC

Female cordset, M8, 4-pin, PVC cable

Description of Sensor Function


The ultrasonic sensor transmits ultrasonic packets in quick succession and responds to their reflection off the detected object. The sensor has a switch output. The switching point is progammable (Teach-In). Objects beyond the taught-in switching point are not detected (background suppression).

Teach-In of Switching Point SP

To teach in a switching point, proceed as follows:

- 1. Connect the sensor and turn on the operating voltage.
- 2. Place the object to be detected at the required distance.
- Connect the teach-in input (ET) to -U_B. This can be done usingthepushbutton or the controller. The LED will start flashing after 3 seconds to indicate that the sensor is ready to start the teach-in process ^(*).
 Disconnect the teach-in input (ET) with -U_B. The switching point SP has now been taught in ^(*).
- If no object is detected within the sensing range of the sensor, the sensor will start flashing at a faster rate. The switching point remains (*) unchanged.

Switching characteristics and display LED



= Object position

Safety Note

The use of this device in applications, where the safety of persons depends from the devices function, is not allowed!



Pepperl+Fuchs Group

www.pepperl-fuchs.com

USA: +1 330 486 0001

fa-info@us.pepperl-fuchs.com

