


Data Sheet

Part Number 856705 1880 MHz SAW Filter

Features


- For Base Station applications
- Usable bandwidth of 60 MHz
- Low loss
- High Attenuation
- • No impedance matching required for operation at 50 Ω
- Single-ended operation
- Ceramic Surface Mount Package (SMP)
- Hermetic
- RoHS compliant (2002/95/EC), Pb-free






Package

Surface Mount 3.00 x 3.00 x 1.22 mm SMP-12



Pin Configuration

Bottom View



Pin No.	Description
2	Input
5	Output
1,3,4,6	Case ground

Dimensions shown are nominal in millimeters All tolerances are ± 0.15 mm except overall length and width ± 0.10 mm

Body: Al₂O₃ ceramic Lid: Kovar, Ni plated Terminations: Au plating 0.5 - 1.0μm, over a 2 – 6μm Ni plating



Data Sheet

Part Number 856705 1880 MHz SAW Filter

Electrical Specifications (1)

Operating Temperature Range: (2) -30 to +85 °C

Parameter (3)	Minimum	Typical (4)	Maximum	Unit
Center Frequency	-	1880	-	MHz
Maximum Insertion Loss				
1850 – 1910 MHz	-	2.2	2.75	dB
Amplitude Variation (5)				
1850 – 1910 MHz	-	0.74	1.6	dB p-p
Amplitude Variation (over any 5MHz band) (5)				
1850 – 1910 MHz	-	0.72	0.8	dB p-p
Stopband Rejection ⁽⁶⁾				
180 – 220 MHz	25	48	-	dB
940 – 1430 MHz	25	36	-	dB
1430 – 1498 MHz	35	39	-	dB
1498 – 1742 MHz	25	35	-	dB
1742 – 1806 MHz	15	22	-	dB
2199 – 2660 MHz	25	32	-	dB
3073 – 3615 MHz	20	33	-	dB
4715 – 5317 MHz	7	24	-	dB
6356 – 7019 MHz	2	14	-	dB
Input/Output VSWR				
1850 – 1910 MHz	-	1.53	2.0	-
Phase Ripple				
1850 – 1910 MHz	-	-	20	deg p-p
Group Delay Ripple				
1850 – 1910 MHz	-		25	ns p-p
Absolute Delay				
1850 – 1910 MHz	-		30	ns
Source Impedance: (7)	-	50	-	Ω
Load Impedance: (7)	-	50	-	Ω

Notes:


- 1. All specifications are based on the TriQuint test circuit shown on page 4
- 2. In production, devices will be tested at room temperature to a guardbanded specification to ensure electrical compliance over temperature
- 3. Electrical margin has been built into the design to account for the variations due to temperature drift and manufacturing tolerances
- 4. Typical values are based on average measurements at room temperature
- 5. Describes the total variation over the defined frequency range
- 6. Stop Band attenuation is relative to maximum insertion loss
- 7. This is the optimum impedance in order to achieve the performance shown

12/08



Part Number 856705 1880 MHz SAW Filter

Typical Performance (at room temperature)






Data Sheet

Part Number 856705 1880 MHz SAW Filter

Matching Schematics


Actual matching values may vary due to PCB layout and parasitics






 $\begin{array}{c} 50~\Omega\\ \text{Single-ended}\\ \text{Output} \end{array}$

Marking




PCB Footprint




The date code consists of: day of the current year (Julian, 3 digits), Y = last digit of the year and M = manufacturing site code

This footprint represents a recommendation only Dimensions shown are nominal in millimeters

Tape and Reel





Dimensions shown are nominal in millimeters Packaging quantity: 5000 units/reel



Part Number 856705 1880 MHz SAW Filter

Data Sheet

Maximum Ratings							
Parameter	Symbol	Minimum	Maximum	Unit			
Operating Temperature Range	Т	-30	+85	_လ			
Storage Temperature Range	T _{stg}	-40	+85	ပ္			
DC voltage on any port (instantaneous only)	-	-	+5	V			
Input Power	P _{in}	-	+22	dBm			

Notes:

1. Input Power is targeted for an applied CW modulated RF signal at 55 °C for 125 hours

Important Notes

Warnings

Electrostatic Sensitive Device (ESD)



Avoid ultrasonic exposure

RoHS Compliance

This product complies with EU directive 2002/95/EC (RoHS)



Solderability

Compatible with JESD22-B102, Pb-free process, 260C peak reflow temperature (see soldering profile)

Links to Additional Technical Information

PCB Layout Tips Qualification Flowchart Soldering Profile

RoHS Information Other Technical Information S-Parameters

TriQuint's liability is limited only to the Surface Acoustic Wave (SAW) component(s) described in this data sheet. TriQuint does not accept any liability for applications, processes, circuits or assemblies, which are implemented using any TriQuint component described in this data sheet.

Contact Information

TriQuint 🐿 SEMICONDUCTOR PO Box 609501 Orlando, FL 32860-9501 USA

Phone: +1 (407) 886-8860 Fax: +1 (407) 886-7061 Email: info-product@tqs.com Web: www.triquint.com

12/08

Or contact one of our worldwide Network of sales offices, Representatives or distributors