



CT238A Amp Clamp Accessory

Current Transformer

This current transformer probe measures AC or DC current. It converts high current to a low level millivolt signal for input directly into a test instrument. It can be used with standard DMMs, recorders, digital or analog meters, data loggers/DAS, oscilloscopes, or other test and measurement instruments.

- AC/DC current clamp, 20 A
- Special "low current" version
- Zero adjust knob

Included Accessories

Attached leads and users manual.

No hassle warranty

No waiting.

*No shipping
charges.*



Our commitment to high-quality products and customer service is demonstrated by our industry exclusive "No Hassle" warranty. In the unlikely event that an Amprobe Test Tool requires warranty service, any of our local dealers are authorized to replace it, on the spot.

(note: \$500 MSLP limit)



N10140

CT238A Amp Clamp Accessory

Data Sheet

General Specifications

Max Conductor Size	19 mm (0.75 in)
Lead Length	1.5 m (59 in)
Power	9 V battery, NEDA 1604, JIS 006P, IEC 6F22
Battery Life	30 hours (alkaline)
Operating Temperature Range	-0 °C to + 50 °C at < 80 % R.H.
Storage Temperature Range	-20 °C to + 85 °C
Temperature Coefficient	0.1 % of rdg per 10 °C
Dimensions	55 mm x 210 mm x 30 mm (2.2 in x 8.3 in x 1.2 in)
Weight	290 g (.64 lb.)
Warranty	One-year

Specifications (23 °C ± 1 °C, < 75 % R.H.)

Function	Range	Accuracy
DC Current		
DC Current	20 A max	±(1% of rdg + 2 mA)
Meter Input Impedance	10 kΩ min. and 100 pF max.	
Division Ratio	10 to 1	
Output	1 A DC at jaws = 100 mV DC to meter	
AC Current		
DC-10 kHz	20 A	20 A (< 1 kHz): ± (1 % of rdg + 2 mA) 20 A (1 to 20 kHz): ± (3 % of rdg + 2 mA)
Meter Input Impedance	10 kΩ min. and 100 pF max.	
Division Ratio	10 to 1	
Output	1 A AC at jaws = 100 mV AC to meter	
Overload Protection		
	500 A	
	300 V AC on uninsulated conductors	

Amprobe® Test Tools
 website: www.Amprobe.com
 email: info@amprobe.com
 Everett, WA 98203
 Tel: 877-AMPROBE

Amprobe® Test Tools Europe
 In den Engematten 14
 79286 Glottertal, Germany
 Tel.: +49 (0) 7684 8009 - 0