## NFC Wire Loop Antenna



Pulse Part Number W7002



The W7002 is a wire loop on plastic carrier product ideal for integration into products such as payment terminal devices or security access and control panels. By design, this antenna can be mounted around LCD or other types of displays, or placed around numeric keypads or control keypads.

The W7002 offers mounting features for machine screws or, with a partnered design approach, snapped into position using snap features. This part can be quickly changed to meet the needs of end-product by changing form-factor, and feeding mechanism.

#### **Features**

- Optimized for metal proximity within the device
- LCD module can be placed inside the antenna perimeter
- Ready mounting features to device mechanics
- Well-known antenna concept ready for production
- RoHS compliant product

#### **Applications**

- Portable and fixed devices
- Payment, sharing, pairing and connect to tags

#### **Standards**

- ISO/IEC 14443 A / B (MIFARE)
- ISO/IEC 18092
- JIS X 6319-4/FeliCa)
- NFCIP-1 / ECMA 3-40

### **Electrical Specifications**

Frequency [MHz]*	13.56
Reading Distance [mm]*	40 EMVCo 35 Grid Scan (avg)
Impedance $[\Omega]^*$	50 / 80
Self Resonance Frequency [MHz]**	89
Inductance [μH]**	0.65
Resistance $[\Omega]^{**}$	0.95
Q-Factor**	57
Matched Q Value***	5-30

## **Environmental Specifications**

Operating Temperature [°C]	-40 to +85
----------------------------	------------

## **Mechanical Specifications**

Color	Black
Dimensions [in/mm]	3.72 x 2.24 x 0.14 (94.6 x 56.8 x 3.65)


**NOTE**: Electrical characteristics depend on distance from metal objects and the location of the antenna on the device. Measured in free space

- \* With matching network
- \*\* Bare coil without any matching network
- \*\*\* With matching network (adjustable). Typical network picture refer to page 2.

San Diego, CA 858 674 8100 Vancouver, WA 360 944 7551 Europe 49 7032 7806 0 Asia 86 755 33966678 North Asia 886 3 4356768 China 86 512 6807 9998

# NFC Wire Loop Antenna

#### Pulse Part Number W7002



Recommended matching network		
Component	Value	Note
Lemc	560 nH	Filter resonance at 15.4 MHz
Cemc	180 pF	Filter resonance at 15.4 MHz
C1	25 pF	Antenna matching component, value depends on the antenna environment Antenna matching
C2 Includes C2a and C2b	180 pF b values)	Antenna matching component, value depends on the antenna environment Antenna matching
Rq	0 Ohm	Rq resistors used to lower Q-value

