



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: +(773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: SMART1500RMXLN

**SmartPro 1.5kVA 1.35kW Line Interactive Extended Run UPS, Sine wave, Pre-installed SNMPWEBCARD, 2U, LCD, USB, Serial, EPO, 120V**

### Highlights

- 1.5kVA / 1500VA / 1350 watt line interactive 2U rack / tower UPS, 0.9 power factor
- 120V nominal output during brownouts to 83V and overvoltages to 145V
- Interactive LCD provides UPS status information and advanced configuration options
- USB, RS232, EPO and Pre-installed SNMPWEBCARD interface
- Expandable runtime, Hot-swap batteries, 95% efficiency, Sine wave output
- 2 independently switchable output load banks
- NEMA 5-15P input, 8 NEMA 5-15R outlets



### Description

Tripp Lite SmartPro Line Interactive UPS with enhanced LCD interface offers network-grade power protection for critical server, network and telecommunications equipment. Line Interactive Uninterruptible Power Supply (UPS) with built-in Auto-Voltage Regulation (AVR) actively corrects brownouts and overvoltages back to usable levels while maintaining a full battery charge in case of power failure. Tripp Lite's unique configuration excels in exceptionally poor-power environments with two separate levels of voltage boost to correct both slight undervoltages and severe brownout conditions. Interactive LCD interface reports UPS operating mode, detailed UPS and site-power data, plus enables a variety of UPS setup and configuration options. Super-fast switchover from line to battery power occurs within milliseconds to maintain operation of connected equipment without interruption or reboot. 95% line-mode efficiency offers reduced heat emissions and operating costs. Network management interfaces support communications via USB, RS-232 and Pre-installed SNMPWEBCARD network interface. HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Network communications ports enable detailed monitoring of equipment load levels, self-test data and utility power conditions. Includes PowerAlert monitoring software and complete cabling. Switched output load banks enable scheduled and real-time remote reboot and load shedding of select outlets. Emergency Power Off (EPO) interface. LCD display panel easily rotates for viewing in rackmount or tower configurations. Audible alarm with push-button momentary alarm-cancel and silent-mode configuration options. Programmable self-test. Field-replaceable, hot-swappable battery modules.

### Package Includes

- SMART1500RMXLN UPS system with Pre-installed SNMPWEBCARD
- PowerAlert software with USB, Serial & EPO cabling
- 4 post installation kit
- Owner's manual

### Features

- Tripp Lite SMART1500RMXLN line interactive 2U rack/tower UPS with 1500VA / 1.5kVA / 1350W capacity and extended runtime options
- Line interactive UPS with Automatic Voltage Regulation (AVR) corrects brownouts and overvoltages from 83 to 145V
- NEMA 5-15P input plug; 8 NEMA 5-15R output receptacles, Two independently switched output load banks
- Maintains uninterrupted operation of connected networking equipment during blackouts, surges, brownouts and overvoltages
- High 95% efficiency rating in line-power mode offers reduced power consumption and BTU emissions
- Internal batteries offer 14 minutes at 50% load (675W) and 4.9 minutes at 100% load (1350W)
- Extended runtime is available with optional BP36V15-2U (limit 1) OR BP36V42-3U (no limit), Output is reduced to 1200 watts maximum with external battery packs
- External battery configurations require the use of Tripp Lite's External Battery Configuration Software (see manual)
- Hot-swappable, user-replaceable internal batteries and external battery packs can be replaced with no disruption to connected equipment
- Front panel LCD monitoring screen with MODE and ENTER buttons reports operating mode with 5-bar battery charge graphic, plus 7 selectable screens of detailed UPS and site power information
- LCD interface also supports a number of advanced user setup and operating preferences

- Ships with 4 post rackmount installation hardware; Optional 2POSTRMKITWM enables 2 post rackmount/wallmount installation; Optional 2-9USTAND enables tower placement
- Built-in USB, RS-232 and Pre-installed SNMPWEBCARD accessory monitoring options
- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- Included PowerAlert UPS monitoring software; Built-in Emergency Power Off (EPO) interface with cable

## Specifications

<b>OUTPUT</b>	
<b>Output Volt Amp Capacity (VA)</b>	1500
<b>Output kVA capacity (kVA)</b>	1.5
<b>Output Watt Capacity (watts)</b>	1350
<b>Output kW capacity</b>	1.35
<b>Output power factor</b>	0.9
<b>Output Capacity Details</b>	Output derates to 1200 watts in all external battery configurations
<b>Nominal Output Voltage(s) Supported</b>	120V
<b>Frequency compatibility</b>	60 Hz
<b>Output voltage regulation (line mode)</b>	-14%, +6%
<b>Output voltage regulation (Battery mode)</b>	+/- 5%
<b>Built-in UPS output receptacles</b>	8 5-15R outlet(s)
<b>Built-in controllable switched load banks</b>	Two switchable two-outlet 5-15R load banks
<b>Output AC waveform (AC mode)</b>	Sine wave
<b>Output AC waveform (battery mode)</b>	Pure Sine wave
<b>INPUT</b>	
<b>Rated input current (at maximum load)</b>	12A
<b>Nominal Input Voltage(s) Supported</b>	120V AC
<b>UPS input connection type</b>	5-15P
<b>Input circuit breaker</b>	15A
<b>UPS Input cord length (ft.)</b>	10
<b>UPS Input cord length (m)</b>	3

<b>Recommended Electrical Service</b>	15A 120V
<b>BATTERY</b>	
<b>Full load runtime (minutes)</b>	4.9 min. (1350w)
<b>Half load runtime (minutes)</b>	14 min. (675w)
<b>Expandable battery runtime</b>	Extended runtime supported via optional external battery packs
<b>External battery pack compatibility</b>	<a href="#">BP36V15-2U</a> (limit 1); <a href="#">BP36V42-3U</a> (multi-pack compatible)
<b>DC system voltage (VDC)</b>	36
<b>Battery recharge rate (included batteries)</b>	Less than 4.5 hours from 10% to 90%
<b>Replacement battery cartridge (internal UPS battery replacement)</b>	<a href="#">RBC93-2U</a>
<b>Battery Access</b>	Front panel battery access door
<b>Battery replacement description</b>	Hot-swappable, user replaceable batteries
<b>VOLTAGE REGULATION</b>	
<b>Voltage regulation description</b>	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145
<b>Overvoltage correction</b>	Input voltages between 127 and 145 are reduced by 12%
<b>Undervoltage correction</b>	Input voltages between 95 and 108 are boosted by 12%
<b>Severe undervoltage correction</b>	Input voltages between 83 and 94 are boosted by 24%
<b>LEDS ALARMS &amp; SWITCHES</b>	
<b>Front panel LCD display</b>	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)
<b>Alarms</b>	Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions
<b>Alarm cancel operation</b>	Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available
<b>Switches</b>	3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions
<b>SURGE / NOISE SUPPRESSION</b>	
<b>UPS AC suppression joule rating</b>	570
<b>UPS AC suppression response time</b>	Instantaneous
<b>EMI / RFI AC noise suppression</b>	Yes
<b>PHYSICAL</b>	

<b>Installation form factors supported with included accessories</b>	4 post 19 inch rackmount
<b>Included mounting accessory description</b>	Adjustable mounting rail kit included
<b>Installation form factors supported with optional accessories</b>	2 post rackmount (2POSTRMKITWM); Wallmount (2POSTRMKITWM); Tower (2-9USTAND)
<b>Primary form factor</b>	Rackmount
<b>UPS / Power Module dimensions in primary form factor (height x width x depth / inches)</b>	3.45 x 17.3 x 13.45
<b>UPS / Power Module dimensions in primary form factor (height x width x depth / cm)</b>	8.8 x 43.9 x 34.2
<b>Rack Height</b>	2U
<b>Secondary form factor</b>	Tower (requires <a href="#">2-9USTAND</a> )
<b>UPS / Power Module weight (lbs)</b>	46.5
<b>UPS / Power Module weight (kg)</b>	21.1
<b>UPS Shipping dimensions (height x width x depth / inches)</b>	8.5 x 23.4 x 19.9
<b>UPS Shipping dimensions (height x width x depth / cm)</b>	21.6 x 59.4 x 50.5
<b>Shipping weight (lbs)</b>	51.3
<b>Shipping weight (kg)</b>	23.3
<b>Cooling method</b>	Fan
<b>UPS housing material</b>	Steel
<b>ENVIRONMENTAL</b>	
<b>Operating Temperature Range</b>	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
<b>Storage Temperature Range</b>	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
<b>Relative Humidity</b>	0 to 95%, non-condensing
<b>AC mode BTU / hr. (full load)</b>	237
<b>COMMUNICATIONS</b>	
<b>Communications interface</b>	USB; DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface

<b>Network monitoring port description</b>	Includes Pre-installed SNMPWEBCARD network interface. Supports detailed monitoring of UPS and site power conditions
<b>PowerAlert software</b>	Included
<b>Communications cable</b>	USB and DB9 cabling included
<b>WatchDog compatibility</b>	Supports Watchdog application, OS and hard-reboot restart options for remote applications
<b>LINE / BATTERY TRANSFER</b>	
<b>Transfer time</b>	4 milliseconds (AC to battery mode), 1 millisecond (Battery to AC mode)
<b>Low voltage transfer to battery power (setpoint)</b>	83
<b>High voltage transfer to battery power (setpoint)</b>	145
<b>SPECIAL FEATURES</b>	
<b>Grounding lug</b>	Back panel grounding lug
<b>Cold Start (startup in battery mode during a power failure)</b>	Cold-start operation supported
<b>High availability UPS features</b>	Hot swappable batteries
<b>Green &amp; high efficiency features</b>	Greater than 95% efficiency - GREEN UPS; Individually controllable load banks
<b>CERTIFICATIONS</b>	
<b>UPS Certifications</b>	Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); Meets FCC Part 15 Category B (EMI); ROHS (Restriction of Hazardous Substances)
<b>WARRANTY</b>	
<b>Product Warranty Period (Worldwide)</b>	2-year warranty, 3 year with <a href="#">registration</a> . Note: <a href="#">registration</a> is required for 3-year warranty.
<b>Connected Equipment Insurance (U.S., Canada &amp; Puerto Rico)</b>	\$250,000 <a href="#">Ultimate Lifetime Insurance</a>

## Related Items

### Optional Products

Related Model	Description	Qty.
<a href="#">WEXT5-500-1500</a>	5-Year Extended Warranty - For Smart Line-Interactive and Online Tower or Rack models, 1500VA or less	1
<a href="#">ENVIROSENSE</a>	Monitors temperature, humidity and contact-closure inputs. (Requires UPS with SNMPWEBCARD, monitored PDU or switched PDU.)	1
<a href="#">SRSWITCH</a>	Magnetic Door Switch Kit for front and rear doors; requires ENVIROSENSE	1
<a href="#">MODBUCARD</a>	For remote monitoring and control via MODBUS protocol	1
<a href="#">2-9USTAND</a>	Enables Tower Placement of Rackmount UPS Systems	1
<a href="#">2POSTRMKITWM</a>	Enables 2-Post Rackmount or Wallmount Installation of Select Rackmount UPS Systems	1
<a href="#">BP36V15-2U</a>	BP36V15-2U - External Battery Pack for UPS System	1

BP36V42-3U	BP36V42-3U - External Battery Pack for UPS System	1
RBC93-2U	2U UPS Replacement Battery Cartridge for select Tripp Lite SmartPro UPS	1
PDUB15	Single-Phase Hot-Swap PDU, 15A 120V, 2U Horizontal Rackmount, 8 NEMA 5-15R outlets, set of 2 NEMA 5-15P input plugs	1
PDU1215	Single-Phase Basic PDU, 15A 120V, 1U Horizontal Rackmount, 13 NEMA 5-15R outlets, NEMA 5-15P input plug	1
PDUNV	Single-Phase Basic PDU, 16A 100-240V, 1U Rackmount, C13 C19 outlets, C20 input and C14, L6-20P, L5-20P, 5-20P and 5-15P adapters	1
PDUV15	Single-Phase Basic PDU, 15A 120V, 0U Vertical Rackmount, 14 NEMA 5-15R outlets, NEMA 5-15P input plug	1
PDUMH15	Single-Phase Metered PDU, 15A 120V, 1U Horizontal Rackmount, 13 NEMA 5-15R outlets, NEMA 5-15P input plug	1
PDUMV15	Single-Phase Metered PDU, 15A 120V, 0U Vertical Rackmount, 16 NEMA 5-15R outlets, NEMA 5-15P input plug	1
PDUMH15AT	Single-Phase Auto Transfer Switch / Metered PDU, 15A 120V, 1U Horizontal Rackmount, 8 NEMA 5-15R outlets, 2 NEMA 5-15P inputs	1
PDUMNH15	Single-Phase Monitored PDU, 15A 120V, 1U Horizontal Rackmount, 8 NEMA 5-15R outlets, NEMA 5-15P input plug	1
PDUMNV15	Single-Phase Monitored PDU, 15A 120V, 0U Vertical Rackmount, 16 NEMA 5-15R outlets, NEMA 5-15P input plug	1
PDUMH15ATNET	Single-Phase Auto Transfer Switch / Switched PDU, 15A 120V, 1U Horizontal Rackmount, 8 NEMA 5-15R outlets, 2 NEMA 5-15P inputs	1
PDUMV15NET	Single-Phase Switched PDU, 15A 120V, 0U Vertical Rackmount, 16 NEMA 5-15R outlets, NEMA 5-15P input plug	1
P007-002	2-ft. Heavy-Duty 14AWG Power cord (IEC-320-C13 to NEMA 5-15P)	1
P007-006	6-ft. Heavy-Duty 14AWG Power cord (IEC-320-C13 to NEMA 5-15P)	1
P007-010	10-ft. Heavy-Duty 14AWG Power cord (IEC-320-C13 to NEMA 5-15P)	1
P010-012	12-ft. 18AWG Power cord (NEMA 5-15P to IEC-320-C13)	1
P022-001	1-ft. 18AWG Power Extension cord (NEMA 5-15R to NEMA 5-15P)	1
P023-001	1-ft. 14AWG Power Adapter cord (NEMA L5-15R to NEMA 5-15P)	1
P034-010	10-ft. 14AWG Heavy Duty Power cord ( IEC-320-C19 to NEMA 5-15P)	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/en/products/model.cfm?txtModelID=5429](http://www.tripplite.com/en/products/model.cfm?txtModelID=5429).

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.