



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: +(773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: OMNISMART700HG

### Omni Smart UPS System - Line-interactive, tower battery backup with hospital grade plug and receptacles

#### Highlights

- 700VA line interactive tower UPS system
- Hospital grade plug and 4 NEMA5-15R hospital grade output receptacles
- Corrects brownouts and overvoltages from 75 to 147V without using battery power
- Enhanced DB9 communications port

#### Description

Tripp Lite's OMNI SMART 700HG offers UPS protection, built-in line interactive voltage regulation, intelligent monitoring and unattended shutdown capability. 700VA power handling capacity supports computers, internetworking equipment and other critical loads during commercial power failures. Line interactive voltage regulation corrects brownouts as low as 75V and overvoltages as high as 147V back to normal 120V levels, saving battery reserves for use only during complete power failures. Includes 4 hospital grade outlets, diagnostic LEDs and built-in DB9 communications port that works with web downloadable PowerAlert Software and cabling to provide automatic unattended shutdown of connected network and PC applications.

#### Applications

- Ideal UPS protection for network workstations, small office file servers and PC systems

#### Package Includes

- OMNI SMART 700HG UPS System
- RS-232 monitoring cable
- Warranty information
- Instruction manual

#### Features

- Ideal UPS protection for mission critical equipment and computers where hospital-grade input/output connections are required
- Provides connected equipment with continuous power during short and long duration loss of commercial power
- Line-interactive voltage regulation corrects brownouts and overvoltages from 75 to 147 volts back to usable 120v output levels, without using battery power
- Hospital-grade plug and outlets offer added degree of safety to input/output connections
- Supports loads up to 700VA/425 watts
- 22 minutes half load runtime (with 350VA load), 9 minutes full load runtime (with 700VA load)
- Hospital grade input plug and 4 NEMA5-15R hospital grade output receptacles
- 1-DB9 serial port for network interface; SNMP compatible
- Surge protection and EMI/RFI noise filtering
- PowerAlert UPS monitoring and auto-shutdown software available for free download from [www.tripplite.com](http://www.tripplite.com)
- Includes complete cabling for remote monitoring via PowerAlert software
- 4 diagnostic LEDs indicate AC present, on battery, voltage correction & battery low/replace
- Battery replacement door
- 2 year product warranty

#### Specifications

<b>OUTPUT</b>
---------------

<b>Frequency compatibility</b>	60 Hz
<b>Output VA</b>	700
<b>Output watts</b>	425
<b>Output nominal voltage</b>	120V nominal
<b>Output voltage regulation</b>	LINE MODE: Sine wave line voltage 120V (-18% / +8%) BATTERY MODE: PWM sine wave output 120V +/-5%
<b>Output frequency regulation</b>	LINE MODE: Passes line frequency of 60Hz +/-10% BATTERY MODE: Inverter output regulated to 60Hz +/-0.5Hz
<b>Outlet quantity / type</b>	4 NEMA5-15R HG
<b>INPUT</b>	
<b>UPS Input cord length (ft.)</b>	6 ft, 14 gauge
<b>Recommended Electrical Service</b>	15A 120V
<b>Maximum Input Amps (A)</b>	3.8
<b>Maximum Input Watts</b>	460
<b>Input connection type</b>	NEMA 5-15P Hospital-Grade
<b>Voltage compatibility (VAC)</b>	120
<b>BATTERY</b>	
<b>DC system voltage (VDC)</b>	12
<b>Battery Access</b>	Battery access door allows hot swap battery replacement without powering connected equipment off
<b>Full load runtime</b>	9 minutes (700VA)
<b>Half load runtime</b>	22 minutes (350VA)
<b>Replacement Battery Cartridge</b>	<a href="#">RBC52</a> (quantity 2)
<b>Typical battery lifespan</b>	3-6 years, depending on usage
<b>Battery charge</b>	2-4 hours to 90%
<b>VOLTAGE REGULATION</b>	
<b>Voltage regulation description</b>	Automatic Voltage Regulation (AVR) circuits maintain clean, regulated computer-grade 120V nominal output, without using battery power, during brownouts to 75V and overvoltages to 147V
<b>Overvoltage correction</b>	Input voltages between 128 and 147V AC are reduced by 12%
<b>Brownout correction</b>	Input voltages between 93 and 107V AC are boosted by 14%
<b>Severe brownout correction</b>	Input voltages between 75 and 92V AC are boosted by 30%
<b>Direct pass through</b>	Input voltages between 108 and 127V AC are passed on to connected equipment unchanged
<b>LEDS ALARMS &amp; SWITCHES</b>	
<b>Alarms</b>	Audible alarm indicates power failure conditions, silenceable via alarm cancel switch. Once cancelled, alarm will resume when approximately 2 minutes of battery operation remain (assuming full load).

<b>Switches</b>	Yes, includes 2 front panel mounted push-button switches for system enable, self-test and alarm cancel functions
<b>Front panel LEDs</b>	4 front-panel indicator LEDs to display line power status, battery power status, battery low/replace status and voltage regulation operation
<b>SURGE / NOISE SUPPRESSION</b>	
<b>EMI / RFI AC noise suppression</b>	Yes
<b>AC suppression response time</b>	Instantaneous
<b>Dataline suppression</b>	-
<b>PHYSICAL</b>	
<b>Shipping weight (lbs)</b>	22
<b>Shipping weight (kg)</b>	10.0
<b>Unit Dimensions (HWD/in)</b>	10.75 x 5.25 x 7.25
<b>Unit Dimensions (HWD/cm)</b>	27.3 x 13.3 x 18.4
<b>Unit weight (lbs)</b>	20
<b>Unit weight (kg)</b>	9.1
<b>Cooling method</b>	Convection
<b>Material of construction</b>	PVC
<b>Form factors supported</b>	Tower
<b>ENVIRONMENTAL</b>	
<b>Relative Humidity</b>	0 to 95%, non-condensing
<b>COMMUNICATIONS</b>	
<b>Network monitoring port</b>	DB9
<b>Software and cabling included</b>	PowerAlert UPS monitoring software available for free download from <a href="http://www.tripplite.com">www.tripplite.com</a> , includes complete RS-232 cabling
<b>LINE / BATTERY TRANSFER</b>	
<b>Transfer time from line power to battery mode</b>	2-4 milliseconds
<b>Low voltage transfer to battery power</b>	75V (resets to line power as voltage increases to 79V)
<b>High voltage transfer to battery power</b>	147V (resets to line power as voltage decreases to 143V)
<b>SPECIAL FEATURES</b>	
<b>Appearance</b>	Attractive gray tower UPS
<b>Cold Start</b>	Yes, inverter can be "cold started" to enable temporary AC output during a power failure
<b>CERTIFICATIONS</b>	
<b>Certifications</b>	Tested to UL1778 (USA, Series AGOM700KSR61), cUL (Canada), FCC Class A (emissions)
<b>WARRANTY</b>	

<b>Product Warranty Period (Worldwide)</b>	2-year limited warranty
<b>Optional Coverage</b>	3 year, 5 year, next day and on-site warranty coverage available

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/en/products/model.cfm?txtModelID=22](http://www.tripplite.com/en/products/model.cfm?txtModelID=22).

---

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.