



Wired Remote Control to switch ON/OFF and monitor battery charger from remote location.

<b>Battery</b>
Charger
Remote
Control

Model 900-RC

## **Design Features**

- Compatible with the following series of Battery Chargers:
- SEC-1250UL, SEC-1280UL
- SEC-2425UL, SEC-2440UL
- Displays operational status and charging stages using colored LEDs
- Provided with 10M / 33' of RJ-45 (8P8C) cable set

## **2 YEAR WARRANTY**

	MODEL NO.	900-RC
DISPLAY	GREEN LED	Marked "Power" – Indicates ON condition
	GREEN LED	Marked "U phase," – Indicates Float Stage
	YELLOW LED	Marked "U₀ phase," – Indicates Boost / Absorption Stage
	RED LED	Marked "I Phase" – Indicates Bulk Stage
CONNECTIONS	INPUT CONNECTOR	RJ-45 Modular Jack (8P8C)
	CONNECTING CABLE SET	8 Conductors, RJ-45 (8P8C) plugs; Straight; Length: 10M / 33'
GENERAL	OPERATING TEMPERATURE	0°C – 40°C / 32°F –104°F
	DIMENSIONS (L x W x H), INCHES	4.28 x 2.55 x 1.02
	DIMENSIONS (L x W x H), MM	108.7 x 64.7 x 25.9
	WEIGHT, LB	0.80
	WEIGHT, KG	0.36