



DC-DC Step Down Converters

Model
SDC-60
60 Amps

Design Features

- Advanced switch mode design
- Mount in almost any location
- Compact and light weight
- Reverse polarity protection
- High efficiency
- Cycle by cycle current limiting circuit
- Over voltage protection
- Short circuit protection

Applications

- Earth moving equipment
- Heavy trucks
- Buses
- Marine vehicles
- CB radios
- 12 Volt lighting systems
- AM / FM sound systems

2 YEAR WARRANTY

MODEL NO.		SDC-60
CAUTION! THERE IS NO ISOLATION BETWEEN THE INPUT AND THE OUTPUT INPUT AND OUTPUT HAVE A COMMON NEGATIVE		
VOLTAGE	INPUT TO OUTPUT ISOLATION	Not isolated. Input and output connections have a common negative
	INPUT VOLTAGE	20 to 35 VDC
	OUTPUT VOLTAGE	13.8 VDC \pm 0.1 V
	OUTPUT VOLTAGE REGULATION	3%
	INPUT CURRENT AT NO LOAD	< 50 mA
OUTPUT CURRENT	CONTINUOUS	60 A
	CURRENT LIMIT *	70 A
ENVIRONMENT	OUTPUT RIPPLE AND NOISE	less than 50 mV RMS
	EFFICIENCY	~ 92%
	OPERATING AMBIENT TEMPERATURE	- 20° to + 30° C (derate linearly to zero at 70° C)
PROTECTIONS	HUMIDITY	Max. 95%, non condensing
	OVERLOAD	By current limiting
	COOLING:	Temperature controlled fan
	OVER HEATING	Drop in output voltage
	REVERSE POLARITY	Fuse protection
	OVER VOLTAGE	Varistor (also protects against load dump)
SAFETY AND EMC STANDARDS	INPUT SIDE FUSE	60 A (2 pieces of 32 V, 30A in parallel)
	EMISSION	EN50081-1
	IMMUNITY	EN50082-1
GENERAL	AUTOMOTIVE DIRECTIVE	95 / 45 / EC
	INPUT / OUTPUT CONNECTIONS	Terminal Block - M6 bolt and nut
	DIMENSIONS, MM (L x W x H)	90 x 93 x 177 2.6
	DIMENSIONS, INCHES (L x W x H)	3.5 x 3.6 x 7
	WEIGHT, KG	1.2
	WEIGHT, LB	2.6

Specifications are subject to change without notice

*NOTE: In current limit condition, the output voltage will drop if the current draw increases beyond the current limit value of 12.5 A

12004-SDC-60-0812