

# SANYO Semiconductors DATA SHEET

An ON Semiconductor Company

N-Channel Silicon MOSFET

# MCH6602 — General-Purpose Switching Device **Applications**

#### **Features**

- · Low ON-resistance
- · Ultrahigh-speed switching
- 1.5V drive
- · Composite type with 2 MOSFETs contained in a single package, facilitating high-density mounting

## **Specifications**


#### Absolute Maximum Ratings at Ta=25°C

Parameter	Symbol	Conditions	Ratings	Unit
Drain-to-Source Voltage	V <sub>DSS</sub>		30	V
Gate-to-Source Voltage	VGSS		±10	V
Drain Current (DC)	ID		0.35	А
Drain Current (Pulse)	IDP	PW≤10μs, duty cycle≤1%	1.4	Α
Allowable Power Dissipation	PD	When mounted on ceramic substrate (900mm <sup>2</sup> ×0.8mm) 1unit	0.8	W
Channel Temperature	Tch		150	C
Storage Temperature	Tstg		-55 to +150	C

This product is designed to "ESD immunity  $< 200V^*$ ", so please take care when handling.

#### **Package Dimensions**

unit: mm (typ) 7022A-006




#### **Product & Package Information**

 Package : MCPH6

• JEITA, JEDEC : SC-88, SC-70-6, SOT-363

• Minimum Packing Quantity : 3,000 pcs./reel


#### Packing Type: TL



#### Marking



#### **Electrical Connection**




<sup>\*</sup> Machine Model

# MCH6602

#### **Electrical Characteristics** at Ta=25°C


Parameter	Symbol	Conditions	Ratings			Unit	
Farameter	Syllibol	Conditions	min	typ	max	Onit	
Drain-to-Source Breakdown Voltage	V(BR)DSS	ID=1mA, VGS=0V	30			V	
Zero-Gate Voltage Drain Current	IDSS	V <sub>DS</sub> =30V, V <sub>GS</sub> =0V			1	μΑ	
Gate-to-Source Leakage Current	IGSS	V <sub>GS</sub> =±8V, V <sub>DS</sub> =0V			±10	μΑ	
Cutoff Voltage	VGS(off)	V <sub>DS</sub> =10V, I <sub>D</sub> =100μA	0.4		1.3	V	
Forward Transfer Admittance	yfs	VDS=10V, ID=80mA	0.15	0.22		S	
Static Drain-to-Source On-State Resistance	R <sub>DS</sub> (on)1	ID=80mA, VGS=4V		2.9	3.7	Ω	
	R <sub>DS</sub> (on)2	ID=40mA, VGS=2.5V		3.7	5.2	Ω	
	R <sub>DS</sub> (on)3	ID=10mA, VGS=1.5V		6.4	12.8	Ω	
Input Capacitance	Ciss			7.0		pF	
Output Capacitance	Coss	V <sub>DS</sub> =10V, f=1MHz		5.9		pF	
Reverse Transfer Capacitance	Crss			2.3		pF	
Turn-ON Delay Time	t <sub>d</sub> (on)			19		ns	
Rise Time	t <sub>r</sub>	Considered Total Circuit		65		ns	
Turn-OFF Delay Time	t <sub>d</sub> (off)	See specified Test Circuit.		155		ns	
Fall Time	tf			120		ns	
Total Gate Charge	Qg			1.58		nC	
Gate-to-Source Charge	Qgs	V <sub>DS</sub> =10V, V <sub>GS</sub> =10V, I <sub>D</sub> =150mA		0.26		nC	
Gate-to-Drain "Miller" Charge	Qgd	]		0.31		nC	
Diode Forward Voltage	V <sub>SD</sub>	I <sub>S</sub> =150mA, V <sub>GS</sub> =0V		0.87	1.2	V	


# **Switching Time Test Circuit**



# **Ordering Information**

Device	Package	Shipping	memo	
MCH6602-TL-E	MCPH6	3,000pcs./reel	Pb Free	






#### **Taping Specification**


#### MCH6602-TL-E


## 1. Packing Format


Package Name   Carrier Tap	Carrier Tape	Maximum Number of devices contained (scs)			Packing format		
	Type	Reel	Inner box	Outer box	Inner BOX (C-1)	Outer BOX (A-7)	
MCPH6	MCP4	3, 000	15, 000	90, 000	5 reels contained Dimensions:mm(external)	6 inner boxes contained Dimensions:mm(external)	
					183×72×185	440×195×210	



## 2. Taping configuration








Those with pin 1 index on the feed hole side ·····TL

# **Outline Drawing**

MCH6602-TL-E

# 

# **Land Pattern Example**



Note on usage: Since the MCH6602 is a MOSFET product, please avoid using this device in the vicinity of highly charged objects.

- Any and all SANYO Semiconductor Co.,Ltd. products described or contained herein are, with regard to "standard application", intended for the use as general electronics equipment. The products mentioned herein shall not be intended for use for any "special application" (medical equipment whose purpose is to sustain life, aerospace instrument, nuclear control device, burning appliances, transportation machine, traffic signal system, safety equipment etc.) that shall require extremely high level of reliability and can directly threaten human lives in case of failure or malfunction of the product or may cause harm to human bodies, nor shall they grant any guarantee thereof. If you should intend to use our products for new introduction or other application different from current conditions on the usage of automotive device, communication device, office equipment, industrial equipment etc., please consult with us about usage condition (temperature, operation time etc.) prior to the intended use. If there is no consultation or inquiry before the intended use, our customer shall be solely responsible for the use.
- Specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Semiconductor Co.,Ltd. assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein.
- Regarding monolithic semiconductors, if you should intend to use this IC continuously under high temperature, high current, high voltage, or drastic temperature change, even if it is used within the range of absolute maximum ratings or operating conditions, there is a possibility of decrease reliability. Please contact us for a confirmation.
- SANYO Semiconductor Co.,Ltd. strives to supply high-quality high-reliability products, however, any and all semiconductor products fail or malfunction with some probability. It is possible that these probabilistic failures or malfunction could give rise to accidents or events that could endanger human lives, trouble that could give rise to smoke or fire, or accidents that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor Co.,Ltd. products described or contained herein are controlled under any of applicable local export control laws and regulations, such products may require the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written consent of SANYO Semiconductor Co.,Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor Co.,Ltd. product that you intend to use.
- Upon using the technical information or products described herein, neither warranty nor license shall be granted with regard to intellectual property rights or any other rights of SANYO Semiconductor Co.,Ltd. or any third party. SANYO Semiconductor Co.,Ltd. shall not be liable for any claim or suits with regard to a third party's intellectual property rights which has resulted from the use of the technical information and products mentioned above.

This catalog provides information as of July, 2012. Specifications and information herein are subject to change without notice.