

Tripp Lite
1111 West 35th Street
Chicago, IL 60609 USA
Telephone: +(773) 869 1234
E-mail: saleshelp@tripplite.com

# Model #: SUDC208V42P

#### 20-60kVA 3 Phase Power Distribution Center



## **Highlights**

- Full size Rack Power Distribution Cabinet supports 20-60kVA 3 phase UPS power distribution in datacenter equipment racks
- 42 pole breaker panel supports 3 phase 208V and single phase 208V and 120V output to connected equipment
- Pre-installed 225A 3 pole main breaker, ground and neutral bars
- Secure front and rear doors, removable side panels
- Full line of accessories includes circuit breakers, corded receptacle whips and PDUs

## **Description**

Tripp Lite's SUDC208V42P Power Distribution Cabinet supports 20-60kVA 3 phase UPS power distribution in critical datacenter equipment racks. Full size rack enclosure with pre-installed 42 pole circuit breaker panel supports 3 phase 208V and single phase 208V and 120V output via optional corded receptacle whips. Breaker panel includes 225A 3 pole main breaker, ground and neutral bars, plus 1/2 and 3/4 inch knockouts. Rack enclosure offers secure front and rear doors, removable side panels and shares common dimensions and overhead wiring tray accessories as Tripp Lite SR42UB rack enclosures. Compatible with Tripp Lite SUBB-series breakers, SUWL-series corded receptacle whips and a full line of compatible basic, metered, monitored and switched PDUs to support a variety of advanced network configurations.

### **Features**

- SUDC208V42P Power Distribution Cabinet supports 20-60kVA 3 Phase UPS power distribution in critical datacenter equipment racks
- Full size rack enclosure with pre-installed 42 pole circuit panel supports 3PH 208V and 1PH 208V and 120V via optional corded receptacle whips
- Line up and match power distribution cabinet blends with existing standard datacenter racks for an aesthetically pleasing appearance while providing convenient connectivity between the centralized 3 phase UPS and protected electronic devices in equipment racks
- Breaker panel includes 225A 3 pole main breaker, ground and neutral bars, 1/2 and 3/4 inch knockouts (see Help & Downloads for manual with detailed wiring information)
- Rack enclosure offers secure front and rear doors, removable side panels and shares common dimensions and overhead wiring tray and ladder accessories as Tripp Lite SR42UB equipment racks
- Requires appropriate SUBB-series output circuit breakers (see Related Items for list of compatible SUBB breakers)
- Optional SUWL-series cable whips and SUWEL-series extensions support a variety of connector types, voltages and cable lengths (see Related Items for list of compatible SUWL-series and SUWEL-series cabling accessories)

#### **Specifications**

| OVERVIEW   |          |
|------------|----------|
| Model Type | Cabinets |
| PHYSICAL   |          |

| Product Warranty Period<br>(Worldwide) | 1-year limited warranty                      |
|--|--|
| WARRANTY                               |  |
| Unit Dimensions (cm)                   | EXTERNAL DIMENSIONS: 199 x 60 x 109 (HWD)    |
| Unit Dimensions (in.)                  | EXTERNAL DIMENSIONS: 78.5 x 23.63 x 43 (HWD) |
| Shipping weight (kg)                   | 156.2  |
| Shipping weight (lbs)                  | 344  |
| Shipping Dimensions<br>(HWD/cm)        | 214 x 70.5 x 119                             |
| Shipping Dimensions<br>(HWD/in)        | 84.5 x 27.75 x 47                            |

# **Related Items**

# **Optional Products**

| Related Model | Description  | Qty. |
|---------------|--|------|
| SUBB120       | 120V 20A Single Phase Circuit Breaker for Rack Distribution Cabinet Applications                                   | 1    |
| SUBB130       | 120V 30A Single Phase Circuit Breaker for Rack Distribution Cabinet Applications                                   | 1    |
| SUBB230       | Single Phase 208V 30A Circuit Breaker for Rack Distribution Cabinet Applications                                   | 1    |
| SUBB320       | Three Phase 208V 20A Circuit Breaker for Rack Distribution Cabinet Applications                                    | 1    |
| SUBB330       | 3 Phase 208V 30A Circuit Breaker for Rack Distribution Cabinet Applications  | 1    |
| SUBB360       | 3 Phase 208V 60A Circuit Breaker for Rack Distribution Cabinet Applications  | 1    |
| SUWEL520C-20  | 120V Single Phase Whip Extension cable in 20 ft. length with L5-20R output and L5-20P input                        | 1    |
| SUWEL520C-3   | 120V Single Phase Whip Extension cable in 3 ft. length with L5-20R output and L5-20P input                         | 1    |
| SUWEL630C-20  | 208/240V Single Phase Whip Extension cable in 20 ft. length with L6-30R output and L6-30P input                    | 1    |
| SUWEL630C-3   | 208/240V Single Phase Whip Extension cable in 3 ft. length with L6-30R output and L6-30P input                     | 1    |
| SUWL520C-10   | 120V Single Phase Whip in 10 ft. length with L5-20R output for Breakered 3 Phase Distribution Cabinet Applications | 1    |
| SUWL520C-15   | 120V Single Phase Whip in 15 ft. length with L5-20R output for Breakered 3 Phase Distribution Cabinet Applications | 1    |
| SUWL520C-20   | 120V Single Phase Whip in 20 ft. length with L5-20R output for Breakered 3 Phase Distribution Cabinet Applications | 1    |
| SUWL520C-25   | 120V Single Phase Whip in 25 ft. length with L5-20R output for Breakered 3 Phase Distribution Cabinet Applications | 1    |
| SUWL520C-30   | 120V Single Phase Whip in 30 ft. length with L5-20R output for Breakered 3 Phase Distribution Cabinet Applications | 1    |
| SUWL520C-35   | 120V Single Phase Whip in 35 ft. length with L5-20R output for Breakered 3 Phase Distribution Cabinet Applications | 1    |
| SUWL520C-40   | 120V Single Phase Whip in 40 ft. length with L5-20R output for Breakered 3 Phase Distribution Cabinet Applications | 1    |
| SUWL520C-5    | 120V Single Phase Whip in 5 ft. length with L5-20R output for Breakered 3 Phase Distribution Cabinet Applications  | 1    |

| SUWL630C-10  | 208/240V Single PHase Whip in 10 ft length with L6-30R output for Breakered 3 Phase Distribution Cabinet Applications | 1 |
|--------------|---|---|
| SUWL630C-15  | 208/240V Single PHase Whip in 15 ft length with L6-30R output for Breakered 3 Phase Distribution Cabinet Applications | 1 |
| SUWL630C-20  | 208/240V Single PHase Whip in 20 ft length with L6-30R output for Breakered 3 Phase Distribution Cabinet Applications | 1 |
| SUWL630C-25  | 208/240V Single PHase Whip in 25 ft length with L6-30R output for Breakered 3 Phase Distribution Cabinet Applications | 1 |
| SUWL630C-30  | 208/240V Single PHase Whip in 30 ft length with L6-30R output for Breakered 3 Phase Distribution Cabinet Applications | 1 |
| SUWL630C-35  | 208/240V Single PHase Whip in 35 ft length with L6-30R output for Breakered 3 Phase Distribution Cabinet Applications | 1 |
| SUWL630C-40  | 208/240V Single PHase Whip in 40 ft length with L6-30R output for Breakered 3 Phase Distribution Cabinet Applications | 1 |
| SUWL630C-5   | 208/240V Single PHase Whip in 5 ft length with L6-30R output for Breakered 3 Phase Distribution Cabinet Applications  | 1 |
| SUWL2120C-5  | 208V Three Phase Whip in 5 ft length with L21-20R output for 3 Phase Distribution Cabinet Applications                | 1 |
| SUWL2120C-10 | 208V Three Phase Whip in 10 ft length with L21-20R output for 3 Phase Distribution Cabinet Applications               | 1 |
| SUWL2120C-15 | 208V Three Phase Whip in 15 ft length with L21-20R output for 3 Phase Distribution Cabinet Applications               | 1 |
| SUWL2120C-20 | 208V Three Phase Whip in 20 ft length with L21-20R output for 3 Phase Distribution Cabinet Applications               | 1 |
| SUWL2120C-25 | 208V Three Phase Whip in 25 ft length with L21-20R output for 3 Phase Distribution Cabinet Applications               | 1 |
| SUWL2120C-30 | 208V Three Phase Whip in 30 ft length with L21-20R output for 3 Phase Distribution Cabinet Applications               | 1 |
| SUWL2120C-35 | 208V Three Phase Whip in 35 ft length with L21-20R output for 3 Phase Distribution Cabinet Applications               | 1 |
| SUWL2120C-40 | 208V Three Phase Whip in 5 ft length with L21-20R output for 3 Phase Distribution Cabinet Applications                | 1 |
| SUWL2130C-5  | 208V Three Phase Whip in 5 ft length with L21-30R output for 3 Phase Distribution Cabinet Applications                | 1 |
| SUWL2130C-10 | 208V Three Phase Whip in 10 ft length with L21-30R output for 3 Phase Distribution Cabinet Applications               | 1 |
| SUWL2130C-15 | 208V Three Phase Whip in 15 ft length with L21-30R output for 3 Phase Distribution Cabinet Applications               | 1 |
| SUWL2130C-20 | 208V Three Phase Whip in 20 ft length with L21-30R output for 3 Phase Distribution Cabinet Applications               | 1 |
| SUWL530C-10  | 120V Single Phase Whip in 10 ft. length with L5-30R output for Breakered 3 Phase Distribution Cabinet Applications    | 1 |
| SUWL530C-15  | 120V Single Phase Whip in 15 ft. length with L5-30R output for Breakered 3 Phase Distribution Cabinet Applications    | 1 |

More information, including related products, owner's manuals, and additional technical specifications, can be found online at www.tripplite.com/en/products/model.cfm?txtModelID=4550.

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.