



Tripp Lite
1111 West 35th Street
Chicago, IL 60609 USA
Telephone: +(773) 869 1234
E-mail: saleshelp@tripplite.com

Model #: B004-VPA2-K-R

KVM Switch - 2-Port Compact PS/2 KVM Switch w/Audio and Cable

Highlights



- Fast, easy switching via keyboard hot keys or push buttons
- Allows sharing of audio components between systems; listen to music from one computer while accessing another
- Compact design saves desk space
- No software or AC adapter required
- (x2) 6ft PS/2 KVM Cable kits and (x2) 6ft 3.5mm Audio Cable Kits included
- Compatible with all major operating systems

Description

The B004-VPA2-K-R is a 2-port Compact PS/2 KVM Switch with optional audio and microphone switching function. It allows you to access, control, boot and reboot two PS/2-enabled computers from a single console (keyboard, monitor and mouse). The independent audio/mic switching function allows an uninterrupted audio experience - you can continue listening to audio even when you switch to the other computer. Compatible with all major operating systems.

Applications

- Use this KVM switch when accessing two PS/2-equipped computers with one monitor, keyboard and mouse.

System Requirements

- Console: VGA, SVGA or Multisync Monitor, PS/2 Keyboard and PS/2 Mouse
- Computers: VGA, SVGA or Multisync Monitor Port, PS/2 Keyboard Port and PS/2 Mouse Port
- Audio (Optional): Speakers with standard 3.5mm Connectors and a computer with 3.5mm ports
- Compatible with all major operating systems




Package Includes

- Compact 2-port PS/2 KVM Switch with Audio
- (2) 6ft PS/2 KVM Cable Kits and (2) 6ft 3.5mm Audio Cable Kits
- Owner's Manual with Warranty Information

Features

- Fast, easy switching via keyboard hot keys or push buttons
- Plug-and-play setup - no software required
- Hot-swap capability allows easy addition or removal of computers without powering down the switch or other computers
- Speaker and microphone connections allow sharing of audio components between systems (standard 3.5 mm audio connections)
- Independent audio switching allows you to listen to audio from one computer while switching to the other computer
- Supports video resolutions up to 2048 x 1536 (standard 15-pin VGA connectors)
- Supports Microsoft® IntelliMouse® and the scrolling wheel on most mice
- Compact design saves desk space
- Does not require an AC adapter
- Compatible with all major operating systems
- Includes two, 6ft Cable Kits

Specifications

OVERVIEW	
# Of Users	1
Console	No
Port Control	Push Buttons, Hotkeys
Max CPU	2
PC/Server	PS/2
Cat5 KVM Switch	No
IP Remote Access	No
PHYSICAL	
Color	Black
Style	Desktop
LCD Monitor (in.)	Not Applicable
LCD Monitor (cm)	Not Applicable
ENVIRONMENTAL	
BTUs	17.065
CONNECTIONS	
Ports	2
Included KVM Cable (Equipment Side) - Connector 1	 HD15 (Male)
Included KVM Cable (Equipment Side) - Connector 2	(x2) MiniDIN6 (Male)
Included KVM Cable (Equipment Side) - Connector 3	 (x2) 3.5mm (Male)
Local Console Ports - Port 1	 HD15 (Female)
Local Console Ports - Port 2	(x2) MiniDIN6 (Female)
Local Console Ports - Port 3	 (x2) 3.5mm (Female)
CERTIFICATIONS	
Certifications	FCC, CE, RoHS Compliant
WARRANTY	
Product Warranty Period (Worldwide)	1-year limited warranty

Related Items

Optional Products

Related Model	Description	Qty.
0DT60002	Minicom - PS/2 to USB Converter	1
B004-DUA2-K-R	KVM Switch - 2-Port Compact DVI/USB KVM Switch w/Audio and Cable	1
B004-VUA2-K-R	KVM Switch - 2-Port Compact USB KVM Switch w/Audio and Cable	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at www.tripplite.com/en/products/model.cfm?txtModelID=3693.

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.