

Digital Megohmmeter

1000V digital tester
With automatic 3 minute test

Features:

- Three test voltages of 250V, 500V and 1000V
- Insulation Resistance to 2000M Ω
- Safety Power Lock enables "hands free" operation for 3 minute test
- Automatic discharge when safety "Press to Test" button is released
- Auto power off and Data Hold
- Large 0.65" (17mm) LCD display
- Full function indication
- Overload protection
- Automatic zero adjustment
- Fast response for both continuity and low resistance testing
- Continuity measurements to 200 Ω and Voltage to 600VAC
- Optional 380399 Resistance Checker to check the performance of your Megohmmeter
- Complete with 6 x AA batteries, heavy duty 2.5ft (0.8m) test leads, alligator clip, large probe, and case with neckstrap



Neckstrap for convenient operation

| Specifications | Range | Basic Accuracy |
|---------------------------------------|------------------------------------|--|
| Insulation Voltage | 250V, 500V, 1000V | |
| Insulation resistance(basic accuracy) | 200M/2000M Ω | <1000M Ω (3%rdg+5d), >1000M Ω (5%rdg+5d) |
| AC Voltage (accuracy) | 600V | (0.8%rdg+3d) |
| Low Resistance | 200 Ω | (1%rdg) |
| Output short circuit current | 1.5 mA 0.3-0.5 mA | |
| Ohmmeter (accuracy) | 20/200 Ω (auto) | (1%rdg+2d) |
| Overload Protection | 2200V (<1 min) | |
| Continuity Beeper | <100 Ω | |
| Dimensions | 3.8 x 6.3 x 2.3" (97 x 160 x 58mm) | |
| Weight | 13oz (369g) | |

Ordering Information:

380360.....Digital Megohmmeter
380360-NIST380360 with Calibration Traceable to NIST

